

N32H7xx Series Errata Sheet

Table of Contents

1.	List of Errata	3
2.	GPIO and AFIO.....	6
2.1.	Digital Filter Cannot Be Enabled When Reading GPIO I/J/K Registers	6
3.	PWR	6
3.1.	Debugger Connection Issue in Sleep Mode	6
4.	AHB Cache.....	6
4.1.	Enabling AHB Cache Causes Legitimate Access to Be Blocked	6
5.	RTC	7
5.1.	RTC Calibration Invalid.....	7
6.	TIMER	7
6.1.	Issue with Switching to 0% Duty Cycle PWM Mode in Force Active Mode	7
7.	I2C	8
8.	Chip Marking and Version Information.....	9
9.	Version History	10
10.	Disclaimer	11

1. List of Errata

Table 1-1 Errata Overview

Errata Lit		Chip Revision			
		A	B	C	D
<p>GPIO and AFIO</p> <p>1.1 Digital Filter Cannot Be Enabled When Reading GPIO I/J/K Registers</p> <p>Description</p> <p>The digital filter function cannot be enabled when reading GPIO I/J/K registers. Digital filters for other alternate functions work normally.</p> <p>Workaround</p> <p>None</p>	<p>Digital Filter Cannot Be Enabled When Reading GPIO I/J/K Registers</p>	<p>•</p>			
<p>2 PWR</p> <p>2.1 Debugger Connection Issue in Sleep Mode</p> <p>Description</p> <p>After the chip enters sleep mode (SLEEP/STOP0/STOP2/STANDBY), the debugger cannot download or</p>					

<p>debug. The chip must exit sleep mode first before using the debugger to download and debug.</p> <p>Workaround</p> <p>None</p> <p>3 AHB Cache</p> <p>3.1 Enabling AHB Cache Causes Legitimate Access to Be Blocked</p> <p>Description</p> <p>When CM4 enables AHB Cache, access permissions for all regions are forcibly changed to match the debugger's access permissions, which causes some legitimate accesses to be blocked, such as certain user APIs that cannot be used.</p> <p>Workaround</p> <p>It is not recommended to enable AHB Cache when using CM4. It is recommended to execute CM4 programs in AHB SRAM, which is 0-wait access SRAM, therefore AHB Cache is not needed.</p>					
---	--	--	--	--	--

<p>4 RTC</p> <p>4.1 RTC Calibration Invalid</p> <p>Description</p> <p>The RTC calibration mode does not work.</p> <p>Workaround</p>					
PWR	Debugger Connection Issue in Sleep Mode	•			
AHB Cache	Enabling AHB Cache Causes Legitimate Access to Be Blocked	•			
RTC	RTC Calibration Invalid	•			
TIMER	Issue with Switching to 0% Duty Cycle PWM Mode in Force Active Mode	•			

•: Issue exists

-: Issue does not exist

2. GPIO and AFIO

2.1. Digital Filter Cannot Be Enabled When Reading GPIO I/J/K Registers

Description

The digital filter function cannot be enabled when reading GPIO I/J/K registers. Digital filters for other alternate functions work normally.

Workaround

None

3. PWR

3.1. Debugger Connection Issue in Sleep Mode

Description

After the chip enters sleep mode (SLEEP/STOP0/STOP2/STANDBY), the debugger cannot download or debug. The chip must exit sleep mode first before using the debugger to download and debug.

Workaround

None

4. AHB Cache

4.1. Enabling AHB Cache Causes Legitimate Access to Be Blocked

Description

When CM4 enables AHB Cache, access permissions for all regions are forcibly changed to match the

debugger's access permissions, which causes some legitimate accesses to be blocked, such as certain user APIs that cannot be used.

Workaround

It is not recommended to enable AHB Cache when using CM4. It is recommended to execute CM4 programs in AHB SRAM, which is 0-wait access SRAM, therefore AHB Cache is not needed.

5. RTC

5.1. RTC Calibration Invalid

Description

The RTC calibration mode does not work.

Workaround

It is recommended to use a precise clock source that does not require calibration, such as LSE.

6. TIMER

6.1. Issue with Switching to 0% Duty Cycle PWM Mode in Force Active Mode

Description

All ATIM/GTIM in force active mode (OC1MD[2:0]=101) cannot properly implement switching to PWM mode with 0% duty cycle.

Workaround

None

7. I2C

Timeout Counter Reset in Debug Mode


Description

When in debug mode and the core is stopped, SMBus timeout can be set to stop or continue normal operation via `DBG_M7/M4APB1FZ.I2CxSTOP`. However, the timeout counter will be reset, causing incorrect timeout values during debugging.

Workaround

None

8. Chip Marking and Version Information



9. Version History

Version	Date	Changes
V1.0.0	2025.4.24	First release

10. Disclaimer

This document is the exclusive property of NSING TECHNOLOGIES PTE. LTD. (Hereinafter referred to as NSING SG). This document, and the product of NSING SG described herein (Hereinafter referred to as the Product) are owned by NSING SG under the laws and treaties of Republic of Singapore and other applicable jurisdictions worldwide. The intellectual properties of the product belong to NSING TECHNOLOGIES INC. (Hereinafter referred to as NSING) and NSING TECHNOLOGIES INC. does not grant any third party any license under its patents, copyrights, trademarks, or other intellectual property rights. Names and brands of third party may be mentioned or referred thereto (if any) for identification purposes only. NSING SG reserves the right to make changes, corrections, enhancements, modifications, and improvements to this document at any time without notice. Please contact NSING SG and obtain the latest version of this document before placing orders. Although NSING has attempted to provide accurate and reliable information, NSING assumes no responsibility for the accuracy and reliability of this document. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. In no event shall NSING be liable for any direct, indirect, incidental, special, exemplary, or consequential damages arising in any way out of the use of this document or the Product. NSING Products are neither intended nor warranted for usage in systems or equipment, any malfunction or failure of which may cause loss of human life, bodily injury or severe property damage. Such applications are deemed, Insecure Usage'. Insecure usage includes, but is not limited to: equipment for surgical implementation, atomic energy control instruments, airplane or spaceship instruments, all types of safety devices, and other applications intended to supporter sustain life. All Insecure Usage shall be made at user's risk. User shall indemnify NSING and hold NSING harmless from and against all claims, costs, damages, and other liabilities, arising from or related to any customer's Insecure Usage Any express or implied warranty with regard to this document or the Product, including, but not limited to. The warranties of merchantability, fitness for a particular purpose and non-infringement are disclaimed to the fullest extent permitted by law. Unless otherwise explicitly permitted by NSING, anyone may not use, duplicate, modify, transcribe or otherwise distribute this document for any purposes, in whole or in part.